



**THE DATASHEET OF  
MAX98310EWL+T**



# MAX98309/MAX98310

## Mono 1.4W Class AB Audio Amplifiers

### General Description

The MAX98309/MAX98310 mono 1.4W class AB audio amplifiers offer low quiescent current while maintaining excellent SNR and low 0.008% THD+N. These ICs feature excellent 90dB PSRR and state of the art click-and-pop suppression.

The ICs are offered with an internally fixed 0dB, 3dB, 6dB, and 9dB gain (MAX98310) or an externally set gain (MAX98309) through external resistors.

The MAX98309 feature a 10ms or 100ms pin-selectable turn-on time, while the MAX98310 has a preset 5ms turn-on time.

The MAX98309/MAX98310 are available in a (1.0mm x 1.0mm) 9-bump, 0.3mm pitch WLP, and are specified over the extended -40°C to +85°C temperature range.

### Applications

Cell Phones/Smartphones  
Digital Cameras  
GPS  
Portable Media Players  
e-Readers  
Tablets


### Benefits and Features

- ◆ **Enhances System Performance**
  - ◇ Differential Input Improves Noise Immunity
  - ◇ Industry-Leading Click-and-Pop Suppression
  - ◇ High 90dB PSRR ( $f_{1N} = 217\text{Hz}$ )
- ◆ **Smaller Solution Size**
  - ◇ 1mm x 1mm WLP Footprint
- ◆ **Extends Battery Life**
  - ◇ Low Quiescent Current
- ◆ **Delivers Robust System Design**
  - ◇ Thermal Overload Protection
  - ◇ Short-Circuit Protection
- ◆ **1.2mA Supply Current ( $V_{DD} = 3.7\text{V}$ )**
- ◆ **750mW into  $8\Omega$  ( $V_{DD} = 3.7\text{V}$ )**
- ◆ **2.5V to 5.5V Supply Operation**
- ◆ **Pin-Selectable, Internally-Fixed Gain (MAX98310)**
- ◆ **1.8V Logic-Compatible SHDN Input**

*Ordering Information appears at end of data sheet.*

*For related parts and recommended products to use with this part, refer to [www.maxim-ic.com/MAX98309.related](http://www.maxim-ic.com/MAX98309.related).*

### Simplified Block Diagram



# MAX98309/MAX98310

## Mono 1.4W Class AB Audio Amplifiers

### ABSOLUTE MAXIMUM RATINGS

$V_{DD}$ to GND.....	-0.3V to 6V	OUT+ to OUT- Short Circuit Duration .....	Continuous
SHDN to GND .....	-0.3V to 6V	Continuous Power Dissipation ( $T_A = +70^\circ\text{C}$ )	
All Other Pins to GND .....	-0.3V to ( $V_{DD} + 0.3\text{V}$ )	WLP (derate 11.9mW/ $^\circ\text{C}$ above $+70^\circ\text{C}$ ).....	848mW
Continuous Current		Junction Temperature .....	+150 $^\circ\text{C}$
$V_{DD}$ , GND, OUT_.....	$\pm 750\text{mA}$	Operating Temperature Range .....	-40 $^\circ\text{C}$ to +85 $^\circ\text{C}$
IN_, SHDN, BIAS, GAIN, TON.....	$\pm 20\text{mA}$	Storage Temperature Range.....	-65 $^\circ\text{C}$ to +150 $^\circ\text{C}$
OUT_ Short Circuit to GND or $V_{DD}$ Duration .....	Continuous	Soldering Temperature (reflow).....	+260 $^\circ\text{C}$

Stresses beyond those listed under "Absolute Maximum Ratings" may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated in the operational sections of the specifications is not implied. Exposure to absolute maximum rating conditions for extended periods may affect device reliability.

### PACKAGE THERMAL CHARACTERISTICS (Note 1)

WLP

Junction-to-Ambient Thermal Resistance ( $\theta_{JA}$ ).....	94 $^\circ\text{C}/\text{W}$
Junction-to-Case Thermal Resistance ( $\theta_{JC}$ ).....	41 $^\circ\text{C}/\text{W}$

**Note 1:** Package thermal resistances were obtained using the method described in JEDEC specification JESD51-7, using a four-layer board. For detailed information on package thermal considerations, refer to [www.maxim-ic.com/thermal-tutorial](http://www.maxim-ic.com/thermal-tutorial).

### ELECTRICAL CHARACTERISTICS

( $V_{DD} = 3.7\text{V}$ ,  $V_{GND} = 0\text{V}$ ,  $\overline{\text{SHDN}} = V_{DD}$ , GAIN =  $V_{DD}$  (0dB),  $C_{BIAS} = 0.1\mu\text{F}$ ,  $C_{IN} = 0.47\mu\text{F}$ , no load:  $R_{IN} = R_F = 10\text{k}\Omega$  (MAX98309),  $T_A = T_{MIN}$  to  $T_{MAX}$ . Typical values are at  $T_A = +25^\circ\text{C}$ , unless otherwise noted.) (Note 2)

PARAMETER	SYMBOL	CONDITIONS	MIN	TYP	MAX	UNITS	
Supply Voltage Range	$V_{DD}$	Guaranteed by PSRR test	2.5		5.5	V	
Undervoltage Lockout	UVLO	$V_{DD}$ falling		1.8	2.3	V	
Quiescent Supply Current	$I_{VDD}$	$\overline{\text{SHDN}} = V_{DD}$	$V_{DD} = 3.7\text{V}$	1.2		mA	
			$V_{DD} = 5\text{V}$	1.9	1.8		
Shutdown Supply Current	$I_{VDD\_SD}$	$\overline{\text{SHDN}} = 0\text{V}$ , $T_A = +25^\circ\text{C}$		2	3	$\mu\text{A}$	
Turn-On Time	$t_{ON}$	MAX98309 shutdown to full operation	TON = GND	10	22.8	ms	
			TON = $V_{DD}$	100			
		MAX98310 shutdown to full operation		5.7	11.5		
Gain	$A_V$	MAX98310	GAIN = $V_{DD}$	-0.25	0	+0.25	dB
			GAIN = GND	2.75	3	3.25	
			GAIN = unconnected	5.75	6	6.25	
			GAIN = BIAS	8.75	9	9.25	
Gain Selection Threshold		MAX98310	GAIN = $V_{DD}$	0.80 x $V_{DD}$		V	
			GAIN = GND	0.05 x $V_{DD}$			
			GAIN = unconnected	0.16 x $V_{DD}$	0.24 x $V_{DD}$		
			GAIN = BIAS	0.35 x $V_{DD}$	0.69 x $V_{DD}$		

# MAX98309/MAX98310

## Mono 1.4W Class AB Audio Amplifiers

### ELECTRICAL CHARACTERISTICS (continued)

( $V_{DD} = 3.7V$ ,  $V_{GND} = 0V$ ,  $\overline{SHDN} = V_{DD}$ ,  $GAIN = V_{DD}$  (0dB),  $C_{BIAS} = 0.1\mu F$ ,  $C_{IN} = 0.47\mu F$ , no load:  $R_{IN} = R_F = 10k\Omega$  (MAX98309),  $T_A = T_{MIN}$  to  $T_{MAX}$ . Typical values are at  $T_A = +25^\circ C$ , unless otherwise noted.) (Note 2)

PARAMETER	SYMBOL	CONDITIONS		MIN	TYP	MAX	UNITS
Differential Input Resistance	$R_{INDIFF}$	MAX98309, $\overline{SHDN} = V_{DD}$		1000		k $\Omega$	
		MAX98310	GAIN = 0dB	38.2			
			GAIN = 3dB	31.7			
			GAIN = 6dB	25.5			
Input Bias Current	$I_{INBIAS}$	MAX98309/MAX98310, $\overline{SHDN} = V_{DD}$			$\pm 1$	$\mu A$	
Shutdown Input Bias Current	$I_{INBIAS\_SHDN}$	$\overline{SHDN} = GND$ , $IN_- = V_{DD}$ or $IN_- = GND$		-5		+5	$\mu A$
Output Offset Voltage	$V_{OS}$	$T_A = +25^\circ C$ (Note 3)			$\pm 0.2$	$\pm 1$	mV
Click-and-Pop Level	$K_{CP}$	$R_L = 8\Omega$ , 32 samples per second, A-weighted, $T_A = +25^\circ C$ (Notes 3, 4)	Into shutdown	-66		dBV	
			Out of shutdown	-66			
Common-Mode Bias Voltage	$V_{BIAS}$	Voltage at BIAS		$0.475 \times V_{DD}$	$0.5 \times V_{DD}$	$0.525 \times V_{DD}$	V
Input Common-Mode Voltage Range	$V_{CM}$	Inferred from CMRR test		0.5		$V_{DD} - 0.6$	V
Common-Mode Rejection Ratio	CMRR	MAX98310/MAX98310	Guaranteed over input common-mode voltage range	-50	-76	dB	
			$f_{IN} = 1kHz$ , $R_L = 8\Omega + 33\mu H$	-62			
Power-Supply Rejection Ratio	PSRR	DC 2.5V to 5.5V		73	93	dB	
		$V_{RIPPLE} = 200mV_{P-P}$ (Note 3)	$f_{IN} = 217Hz$	90			
			$f_{IN} = 1kHz$	90			
			$f_{IN} = 10kHz$	72			
Output Power	$P_{OUT}$	$V_{DD} = 3.7V$ , 1% THD+N	$R_L = 8\Omega + 68\mu H$	0.750		W	
			$R_L = 4\Omega + 33\mu H$	1.2			
		$V_{DD} = 3.7V$ , 10% THD+N	$R_L = 8\Omega + 68\mu H$	0.9			
			$R_L = 4\Omega + 33\mu H$	1.5			
		$V_{DD} = 5V$ , 1% THD+N (Note 5)	$R_L = 8\Omega + 68\mu H$	1.4			
			$R_L = 4\Omega + 33\mu H$ , thermally limited	2.1			
		$V_{DD} = 5V$ , 10% THD+N (Note 5)	$R_L = 8\Omega + 68\mu H$	1.7			
			$R_L = 4\Omega + 33\mu H$ , thermally limited	2.7			

# MAX98309/MAX98310

## Mono 1.4W Class AB Audio Amplifiers

### ELECTRICAL CHARACTERISTICS (continued)

( $V_{DD} = 3.7V$ ,  $V_{GND} = 0V$ ,  $\overline{SHDN} = V_{DD}$ ,  $GAIN = V_{DD}$  (0dB),  $C_{BIAS} = 0.1\mu F$ ,  $C_{IN} = 0.47\mu F$ , no load:  $R_{IN} = R_F = 10k\Omega$  (MAX98309),  $T_A = T_{MIN}$  to  $T_{MAX}$ . Typical values are at  $T_A = +25^\circ C$ , unless otherwise noted.) (Note 2)

PARAMETER	SYMBOL	CONDITIONS	MIN	TYP	MAX	UNITS
Total Harmonic Distortion Plus Noise	THD+N	$f_{IN} = 1kHz$ , BW = 22Hz to 22kHz $R_L = 8\Omega + 68\mu H$ , $P_{OUT} = 375mW$		0.008		%
		$R_L = 4\Omega + 33\mu H$ , $P_{OUT} = 750mW$	0.06	0.02		
		$f_{IN} = 6kHz$ , BW = 22Hz to 22kHz $R_L = 8\Omega + 68\mu H$ , $P_{OUT} = 375mW$		0.01		
Signal-to-Noise Ratio	SNR	A-weighted, $V_{DD} = 5V$ , $P_{OUT} = 1.4W$ , $R_L = 8\Omega + 33\mu H$		110		dB
Output Noise Voltage	$V_N$	A-weighted (Note 3)		9		$\mu V$
Overcurrent Protection Threshold				2		A
Thermal-Protection Threshold				+160		$^\circ C$
Thermal-Protection Hysteresis				15		$^\circ C$
Maximum Capacitive Load Drive	$C_L$	Bridge-tied load capacitance		500		pF
<b>LOGIC INPUT (<math>\overline{SHDN}</math>, TON) (MAX98309)</b>						
Input Logic-High	$V_{IH}$	1.8V logic compliant	1.4			V
Input Logic-Low	$V_{IL}$	1.8V logic compliant			0.4	V
Input Leakage Current High	$I_{IH}$	$T_A = +25^\circ C$			1	$\mu A$
Input Leakage Current Low	$I_{IL}$	$T_A = +25^\circ C$			1	$\mu A$

**Note 2:** All specifications are 100% tested at  $T_A = +25^\circ C$ ; temperature limits are guaranteed by design.

**Note 3:** Inputs AC-coupled to GND.


**Note 4:** Mode transitions controlled by  $\overline{SHDN}$ .

**Note 5:** Thermally limited by package.

## Mono 1.4W Class AB Audio Amplifiers

### Typical Operating Characteristics

( $V_{DD} = 3.7V$ ,  $V_{GND} = 0V$ ,  $\overline{SHDN} = V_{DD}$ , GAIN = GND ( $R_F = R_{IN} = 10k\Omega$ ),  $C_{BIAS} = 0.1\mu F$ ,  $C_{IN} = 1\mu F$ , no load, unless otherwise noted.)









# MAX98309/MAX98310

## Mono 1.4W Class AB Audio Amplifiers

### Typical Operating Characteristics (continued)








( $V_{DD} = 3.7V$ ,  $V_{GND} = 0V$ ,  $\overline{SHDN} = V_{DD}$ , GAIN = GND ( $R_F = R_{IN} = 10k\Omega$ ),  $C_{BIAS} = 0.1\mu F$ ,  $C_{IN} = 1\mu F$ , no load, unless otherwise noted.)



## Mono 1.4W Class AB Audio Amplifiers

### Typical Operating Characteristics (continued)

( $V_{DD} = 3.7V$ ,  $V_{GND} = 0V$ ,  $\overline{SHDN} = V_{DD}$ , GAIN = GND ( $R_F = R_{IN} = 10k\Omega$ ),  $C_{BIAS} = 0.1\mu F$ ,  $C_{IN} = 1\mu F$ , no load, unless otherwise noted.)










# MAX98309/MAX98310

## Mono 1.4W Class AB Audio Amplifiers

### Typical Operating Characteristics (continued)


( $V_{DD} = 3.7V$ ,  $V_{GND} = 0V$ ,  $\overline{SHDN} = V_{DD}$ , GAIN = GND ( $R_F = R_{IN} = 10k\Omega$ ),  $C_{BIAS} = 0.1\mu F$ ,  $C_{IN} = 1\mu F$ , no load, unless otherwise noted.)



# MAX98309/MAX98310

## Mono 1.4W Class AB Audio Amplifiers

### Pin Configurations



### Pin Descriptions

PIN		NAME	FUNCTION
MAX98309	MAX98310		
A1	A1	OUT+	Amplifier Positive Output
A2	A2	$\overline{\text{SHDN}}$	Active-Low Shutdown Input. Connect to GND to place the IC into shutdown. Connect to $V_{DD}$ for normal operation.
A3	A3	IN-	Inverting Audio Input
B1	B1	GND	Ground
B2	—	TON	Turn-On Time Selection. Connect TON to GND for a 10ms turn-on time. Connect TON to $V_{DD}$ for a 100ms turn on time.
—	B2	GAIN	Gain Select Input. See <a href="#">Table 1</a> for gain settings.
B3	B3	$V_{DD}$	Power Supply Input. Connect a 1 $\mu$ F capacitor from $V_{DD}$ to GND.
C1	C1	OUT-	Amplifier Negative Output
C2	C2	BIAS	Common-Mode DC Bias Bypass. Connect a 0.1 $\mu$ F (min) capacitor to GND.
C3	C3	IN+	Noninverting Audio Input

# MAX98309/MAX98310

## Mono 1.4W Class AB Audio Amplifiers

### Detailed Description

The MAX98309/MAX98310 mono 1.4W Class AB audio amplifiers offer low quiescent current while maintaining excellent SNR and low 0.008% THD+N. Both ICs feature excellent 90dB PSRR and state-of-the-art click-and-pop suppression.

The ICs are offered with an internally fixed 0dB, 3dB, 6dB, and 9dB gain (MAX98310) or an externally set gain (MAX98309) through external resistors.

The MAX98309 features a 10ms or 100ms pin-selectable turn-on time, while the MAX98310 has a preset 5ms turn-on time.

#### Bias

The ICs operate from a single 2.5V to 5.5V power supply and feature an internally generated common-mode bias voltage of  $V_{DD}/2$  reference to ground. BIAS provides both click-and-pop suppression and sets the DC bias level for the audio outputs. Choose the value of the bypass capacitor as described in the [BIAS Capacitor](#) section. Do not connect external loads to BIAS as this can affect the overall performance.

#### Turn-On Time

The MAX98309 external gain amplifier features a selectable turn-on time for optimized click-and-pop performance. Connect TON to GND for a 10ms turn-on time. Connect TON to  $V_{DD}$  for a 100ms turn-on time. The MAX98310 has a preset 5ms turn-on time.

#### Shutdown Mode

The ICs feature a 1.8 $\mu$ A low-power shutdown mode that reduces quiescent current consumption. When the active-low shutdown mode is entered, the ICs' internal bias circuitry is disabled, the amplifier outputs go high impedance, and BIAS is driven to GND.

#### Click-and-Pop Suppression

The ICs feature Maxim's industry-leading click-and-pop suppression circuitry. During startup, the amplifier common-mode bias voltage ramps to the DC bias point. When entering shutdown, the amplifier outputs are high impedance between both outputs. This scheme minimizes the energy present in the audio band.

### Applications Information

#### BTL Amplifier

The ICs are designed to drive a load differentially, a configuration referred to as bridge-tied load, or BTL. The BTL configuration ([Figure 1](#)) offers advantages over the single-ended configuration, where one side of the load is connected to ground. Driving the load differentially doubles the output voltage compared to a single-ended amplifier under similar conditions.

Substituting  $2 \times V_{OUT(P-P)}$  for  $V_{OUT(P-P)}$  into the following equations yields four times the output power due to doubling of the output voltage:

$$V_{RMS} = \frac{V_{OUT(P-P)}}{2\sqrt{2}}$$
$$P_{OUT} = \frac{V_{RMS}^2}{R_L}$$

Because the differential outputs are biased at midsupply, there is no net DC voltage across the load. This eliminates the need for DC-blocking capacitors required for single-ended amplifiers. These capacitors can be large, expensive, consume board space, and degrade low-frequency performance.

#### Power Dissipation and Heatsinking

Under normal operating conditions, the ICs dissipate a significant amount of power. The maximum power dissipation is given in the [Absolute Maximum Ratings](#) or can be calculated by the following equation:

$$P_{D(MAX)} = \frac{T_{J(MAX)} - T_A}{\theta_{JA}}$$

where  $T_{J(MAX)}$  is +150°C,  $T_A$  is the ambient temperature, and  $\theta_{JA}$  is the reciprocal of the derating factor in C/W as specified in the [Absolute Maximum Ratings](#).




Figure 1. BTL Configuration

## Mono 1.4W Class AB Audio Amplifiers

The increase in power delivered by the BTL configuration directly results in an increase in internal power dissipation over the single-ended configuration. The maximum internal power dissipation for a given  $V_{DD}$  and load is given by the following equation:

$$P_{D(MAX)} = \frac{2V_{DD}^2}{\pi^2 R_L}$$

If the internal power dissipation for a given application exceeds the maximum allowed for a given package, reduce power dissipation by increasing the ground plane heatsinking capability and the size of the traces to the device. See the [Layout and Grounding](#) section. Other methods for reducing power dissipation are to reduce  $V_{DD}$ , increase load impedance, decrease ambient temperature, reduce gain, or reduce input signal.

Thermal-overload protection limits total power dissipation in the MAX98309/MAX98310. When the junction temperature exceeds +160°C, the thermal protection circuitry disables the amplifier. Operation returns to normal once the die cools by 15°C.

### Amplifier Gain

#### Fixed Differential Gain (MAX98310)

The MAX98310 features four internally fixed differential gain options selectable by GAIN ([Table 1](#)). This simplifies design, decreases required application footprint size, and eliminates external gain-setting resistors.

#### External Differential Gain (MAX98309)

The MAX98309 features an external gain option. Resistors  $R_F$  and  $R_{IN}$ . See the [Simplified Block Diagram](#) and set the gain of the amplifier as follows:

$$A_V = \frac{R_F}{R_{IN}}$$

where  $A_V$  is the desired voltage gain. Hence, an  $R_{IN}$  of 10k $\Omega$  and an  $R_F$  of 20k $\Omega$  yields a gain of 2V/V or 6dB.  $R_F$  can be either fixed or variable, allowing the use of a digitally controlled potentiometer to alter the gain under software control.

**Table 1. Fixed Differential Gain**

GAIN CONNECTION	GAIN (dB)
$V_{DD}$	0
GND	3
Unconnected	6
BIAS	9

### Input Filter

The fully differential amplifier inputs can be biased at voltages other than midsupply. The common-mode feedback circuit adjusts for input bias, ensuring the outputs are still biased at midsupply. Input capacitors are not required as long as the input voltage is within the specified common-mode range listed in the [Electrical Characteristics](#) table.

If input capacitors are used, input capacitor  $C_{IN}$ , in conjunction with the input resistor  $R_{IN}$ , forms a highpass filter that removes the DC bias from an incoming signal. The AC-coupling capacitor allows the amplifier to bias the signal to an optimum DC level. Assuming zero-source impedance, the -3dB point of the highpass filter is given by:

$$f_{-3dB} = \frac{1}{2\pi R_{IN} C_{IN}}$$

Setting  $f_{-3dB}$  too high affects the low-frequency response of the amplifier. Use capacitors with adequately low voltage coefficients, such as X7R ceramic capacitors with a high voltage rating. Capacitors with higher voltage coefficients result in increased distortion at low frequencies.

### BIAS Capacitor

BIAS is the output of the internally generated  $V_{DD}/2$  bias voltage. The BIAS bypass capacitor,  $C_{BIAS}$ , improves PSRR and THD+N by reducing power supply and other noise sources at the common-mode bias node, and also generates the clickless/popless startup DC bias waveform for the speaker amplifiers. Bypass BIAS with a 0.1 $\mu$ F capacitor to GND. Larger values of  $C_{BIAS}$  (up to 1 $\mu$ F) improve PSRR.

### Supply Bypassing

Proper power-supply bypassing ensures low-noise, low-distortion performance. Connect a 1 $\mu$ F ceramic capacitor from  $V_{DD}$  to GND. Add additional bulk capacitance as required by the application. Locate the bypass capacitor as close as possible to the device.

### Layout and Grounding

Good PCB layout is essential for optimizing performance. Use large traces for the power-supply inputs and amplifier outputs to minimize losses due to parasitic trace resistance and route heat away from the device. Good grounding improves audio performance, and prevents any digital switching noise from coupling into the audio signal.

# MAX98309/MAX98310

## Mono 1.4W Class AB Audio Amplifiers

### Ordering Information

PART	TEMP RANGE	GAIN	PIN-PACKAGE	TOP MARK
MAX98309EWL+	-40°C to +85°C	External	9 WLP	+AIY
MAX98310EWL+	-40°C to +85°C	Fixed	9 WLP	+AIZ

+Denotes a lead(Pb)-free/RoHS-compliant package.


# MAX98309/MAX98310

## Mono 1.4W Class AB Audio Amplifiers


### Package Information

For the latest package outline information and land patterns (footprints), go to [www.maxim-ic.com/packages](http://www.maxim-ic.com/packages). Note that a "+", "#", or "-" in the package code indicates RoHS status only. Package drawings may show a different suffix character, but the drawing pertains to the package regardless of RoHS status.

PACKAGE TYPE	PACKAGE CODE	OUTLINE NO.	LAND PATTERN NO.
9 WLP (0.3mm pitch)	W91D1+1	<a href="#">21-0486</a>	Refer to <a href="#">Application Note 1891</a>




TOP VIEW



SIDE VIEW

COMMON DIMENSIONS	
A	0.64 ±0.05
A1	0.16 ±0.03
A2	0.48 REF
A3	0.025 BASIC
b	0.21 ±0.03
D1	0.60 BASIC
E1	0.60 BASIC
e	0.30 BASIC
SD	0.00 BASIC
SE	0.00 BASIC

PKG. CODE	E		D		DEPOPULATED BUMPS
	MIN	MAX	MIN	MAX	
W91D1+1	0.95	0.98	0.95	0.98	NONE



BOTTOM VIEW

**NOTES:**

- Terminal pitch is defined by terminal center to center value.
- Outer dimension is defined by center lines between scribe lines.
- All dimensions in millimeter.
- Marking shown is for package orientation reference only.
- Tolerance is ± 0.02 unless specified otherwise.
- All dimensions apply to PbFree (+) package codes only.
- Front - side finish can be either Black or Clear.

<b>MAXIM</b>			
TITLE PACKAGE OUTLINE 9 BUMPS, WLP PKG. 0.3mm PITCH			
APPROVAL	DOCUMENT CONTROL NO. 21-0486	REV. B	1/1

-DRAWING NOT TO SCALE-

# MAX98309/MAX98310

## Mono 1.4W Class AB Audio Amplifiers

### *Revision History*



REVISION NUMBER	REVISION DATE	DESCRIPTION	PAGES CHANGED
0	6/11	Initial release	—

*Maxim cannot assume responsibility for use of any circuitry other than circuitry entirely embodied in a Maxim product. No circuit patent licenses are implied. Maxim reserves the right to change the circuitry and specifications without notice at any time. The parametric values (min and max limits) shown in the Electrical Characteristics table are guaranteed. Other parametric values quoted in this data sheet are provided for guidance.*

**Maxim Integrated Products, 120 San Gabriel Drive, Sunnyvale, CA 94086 408-737-7600 \_\_\_\_\_ 14**

## Looking for pricing, stock, or lifecycle information?

Click below to explore more details on WIN SOURCE:

-  [View MAX98310EWL+T on WIN SOURCE](#)
-  [Maxim Integrated Information](#)

## Optimize Your Supply Chain with WIN SOURCE Solutions

-  Global Sourcing Solution
-  Obsolete Management
-  Cost Control Management
-  Shortage Management
-  Alternative Solution
-  Excess Inventory Management