



**THE DATASHEET OF
SBSPP0500683MXB**



Dimensions

| | |
|----|---------------------------|
| L | 3.20±0.3 (0.126"±0.012") |
| W | 1.65±0.3 (0.065"±0.012") |
| T | 1.60±0.20 (0.063"±0.008") |
| B1 | 0.95±0.3 (0.037"±0.012") |
| B2 | 0.50±0.25 (0.020"±0.010") |



Suggested mounting pad details

E = Unprinted solder area between ground pads



| | |
|---|---------------|
| A | 1.20 (0.047") |
| B | 0.90 (0.035") |
| C | 0.60 (0.024") |
| D | 0.80 (0.030") |
| E | 1.00 (0.039") |
| F | 2.90 (0.114") |

It is recommended that designers independently confirm pad dimensions are acceptable, particularly with respect to higher working voltages.

Electrical Details

| | |
|------------------------------|-----------------|
| Electrical Configuration | Pi Filter |
| Capacitance Measurement | @ 1000hr Point |
| Current Rating | 1A |
| Insulation Resistance (IR) | 10GΩ or 1000ΩF |
| Temperature Rating | -55°C to +125°C |
| Ferrite Inductance (Typical) | 0.30μH (@ 1MHz) |



Mechanical Details

| | |
|---------------------------------|--|
| Terminals & Finish - End & Side | Sn plated over FlexiCap™ Termination |
| Construction | Ceramic Multi Layer Chip Capacitor Multi Layer Ferrite Bead Inductor Connection via FlexiCap™ Termination |
| Weight (Typical) | 0.07g (0.0025oz) |

Reeled quantities

| | |
|-----------------|--------------|
| | SBSPP |
| 178mm (7") reel | 1500 |

| Product Code | Capacitance (±20%) | Dielectric | Rated Voltage (dc) | DWV (dc) | Approximate Resonant Frequency (MHz) | Typical No-Load Insertion Loss (dB)* | | | | |
|----------------|--------------------|------------|--------------------|----------|--------------------------------------|--------------------------------------|------|-------|--------|------|
| | | | | | | 0.1MHz | 1MHz | 10MHz | 100MHz | 1GHz |
| SBSPP1000220MC | 22pF | COG/NPO | 100 | 250 | 1000 | 0 | 0 | 0 | 2 | 22 |
| SBSPP1000470MC | 47pF | | 100 | 250 | 620 | 0 | 0 | 0 | 4 | 16 |
| SBSPP1000101MC | 100pF | | 100 | 250 | 400 | 0 | 0 | 0 | 7 | 14 |
| SBSPP1000221MC | 220pF | | 100 | 250 | 260 | 0 | 0 | 1 | 14 | 12 |
| SBSPP1000471MC | 470pF | | 100 | 250 | 180 | 0 | 0 | 2 | 25 | 16 |
| SBSPP1000102MX | 1.0nF | X7R | 100 | 250 | 120 | 0 | 0 | 4 | 37 | 16 |
| SBSPP1000152MX | 1.5nF | | 100 | 250 | 90 | 0 | 0 | 7 | 37 | 16 |
| SBSPP1000222MX | 2.2nF | | 100 | 250 | 72 | 0 | 0 | 9 | 37 | 16 |
| SBSPP1000332MX | 3.3nF | | 100 | 250 | 59 | 0 | 1 | 13 | 37 | 16 |
| SBSPP1000472MX | 4.7nF | | 100 | 250 | 50 | 0 | 2 | 14 | 37 | 16 |
| SBSPP1000682MX | 6.8nF | | 100 | 250 | 38 | 0 | 4 | 24 | 37 | 16 |
| SBSPP1000103MX | 10nF | | 100 | 250 | 33 | 0 | 5 | 24 | 37 | 16 |
| SBSPP1000153MX | 15nF | | 100 | 250 | 26 | 0 | 8 | 32 | 37 | 16 |
| SBSPP0500223MX | 22nF | | 50 | 125 | 21 | 0 | 10 | 38 | 37 | 16 |
| SBSPP0500333MX | 33nF | | 50 | 125 | 17 | 1 | 13 | 46 | 37 | 16 |
| SBSPP0500473MX | 47nF | | 50 | 125 | 13 | 2 | 16 | 50 | 37 | 16 |
| SBSPP0500683MX | 68nF | | 50 | 125 | 10 | 3 | 20 | 54 | 37 | 16 |
| SBSPP0500104MX | 100nF | | 25 | 67.5 | 8.5 | 6 | 19 | 52 | 37 | 16 |
| SBSPP0500154MX | 150nF | | 25 | 67.5 | 7 | 8 | 24 | 56 | 37 | 16 |

* Insertion Loss performance quoted is measured on an open FR4 board mounted on a brass backplane in a 50Ω system. Performance curves can be supplied on request. Performance in circuit is liable to be different and is affected by board material, track layout, grounding efficiency and circuit impedances. Shielding can be used to improve high frequency performance.

Ordering Information - SBSPP range

| SB | S | P | P | 100 | 0153 | M | X | B |
|--------------------|---------------|------------------------------|--------------------------|--------------------------------------|--|-----------|------------------------|---|
| Type | Case style | Size | Electrical configuration | Voltage (dc) | Capacitance in picofarads (pF) | Tolerance | Dielectric | Packaging |
| Syfer Board Filter | Surface Mount | Size Code P (nominally 1206) | P = Pi Filter | 025 = 25V 050 = 50V 100 = 100V | First digit is 0. Second and third digits are significant figures of capacitance code. The fourth digit is number of zeros following Example: 0472 = 4700pF 0153 = 15000pF | M = ±20% | C = COG/NPO X = X7R | T=178mm (7") reel R=330mm (13") reel B = Bulk |

Note: The addition of a 4-digit numerical suffix code can be used to denote changes to the standard part. Options include for example: change of finish / alternative voltage rating / non-standard intermediate capacitance values / test requirements. Please refer specific requests to the factory.

Looking for pricing, stock, or lifecycle information?

Click below to explore more details on WIN SOURCE:

 [View SBSPP0500683MXB on WIN SOURCE](#)

 [Knowles Syfer](#) Information

Optimize Your Supply Chain with WIN SOURCE Solutions

-  Global Sourcing Solution
-  Obsolete Management
-  Cost Control Management
-  Shortage Management
-  Alternative Solution
-  Excess Inventory Management