THE DATASHEET OF

MAX40007ANT+

PNP Silicon AF Transistor



- Low collector-emitter saturation voltage
- Complementary type: SMBTA06 / MMBTA06(NPN)
- Pb-free (RoHS compliant) package
- Qualified according AEC Q101

AEC Qualified RoHS

Type	Marking	Pin Configuration			Package
SMBTA56/MMBTA56	s2G	1=B	2=E	3=C	SOT23

Maximum Ratings

Parameter	Symbol	Value	Unit
Collector-emitter voltage	V_{CEO}	80	V
Collector-base voltage	V_{CBO}	80	
Emitter-base voltage	V_{EBO}	4	
Collector current	I_C	500	mA
Peak collector current, $t_p \leq 10$ ms	I_{CM}	1	A
Base current	I_B	100	mA
Peak base current	I_{BM}	200	
Total power dissipation- $T_S \leq 79$°C	P_{tot}	330	mW
Junction temperature	T_j	150	°C
Storage temperature	T_{stg}	-65 ... 150	

Thermal Resistance

Parameter	Symbol	Value	Unit
Junction - soldering point[1)]	R_{thJS}	≤ 215	K/W

[1]For calculation of R_{thJA} please refer to Application Note AN077 (Thermal Resistance Calculation)

Electrical Characteristics at T_A = 25°C, unless otherwise specified

Parameter	Symbol	Values			Unit
		min.	typ.	max.	
DC Characteristics					
Collector-emitter breakdown voltage I_C = 1 mA, I_B = 0	$V_{(BR)CEO}$	80	-	-	V
Collector-base breakdown voltage I_C = 100 µA, I_E = 0	$V_{(BR)CBO}$	80	-	-	
Emitter-base breakdown voltage I_E = 10 µA, I_C = 0	$V_{(BR)EBO}$	4	-	-	
Collector-base cutoff current V_{CB} = 80 V, I_E = 0 V_{CB} = 80 V, I_E = 0 , T_A = 150 °C	I_{CBO}	 - -	 - -	 0.1 20	µA
Collector-emitter cutoff current V_{CE} = 60 V, I_B = 0	I_{CEO}	-	-	0.1	
DC current gain[1)] I_C = 10 mA, V_{CE} = 1 V I_C = 100 mA, V_{CE} = 1 V	h_{FE}	 100 100	 - -	 - -	-
Collector-emitter saturation voltage[1)] I_C = 100 mA, I_B = 10 mA	V_{CEsat}	-	-	0.25	V
Base-emitter voltage[1)] I_C = 100 mA, V_{CE} = 1 V	$V_{BE(ON)}$	-	-	1.2	
AC Characteristics					
Transition frequency I_C = 20 mA, V_{CE} = 5 V, f = 20 MHz	f_T	-	100	-	MHz
Collector-base capacitance V_{CB} = 10 V, f = 1 MHz	C_{cb}	-	7	-	pF

[1]Pulse test: t < 300µs; D < 2%

DC current gain $h_{FE} = f(I_C)$

V_{CE} = 1 V



Collector-emitter saturation voltage

$I_C = f(V_{CEsat})$, h_{FE} = 10



Base-emitter saturation voltage

$I_C = f(V_{BEsat})$, h_{FE} = 10



Collector current $I_C = f(V_{BE})$

V_{CE} = 1V



Collector cutoff current I_{CBO} = $f(T_A)$

V_{CB} = 80 V



Transition frequency f_T = $f(I_C)$

V_{CE} = parameter in V, f = 2 GHz



Collector-base capacitance C_{cb} = $f(V_{CB})$

Emitter-base capacitance C_{eb} = $f(V_{EB})$



Total power dissipation P_{tot} = $f(T_S)$



Permissible Pulse Load $R_{thJS} = f(t_p)$



Permissible Pulse Load

$P_{totmax}/P_{totDC} = f(t_p)$



Package Outline



1) Lead width can be 0.6 max. in dambar area

Foot Print



Marking Layout (Example)



Standard Packing

Reel ø180 mm = 3.000 Pieces/Reel
Reel ø330 mm = 10.000 Pieces/Reel



Edition 2009-11-16

Published by
Infineon Technologies AG
81726 Munich, Germany

© 2009 Infineon Technologies AG
All Rights Reserved.

Legal Disclaimer

The information given in this document shall in no event be regarded as a guarantee of conditions or characteristics. With respect to any examples or hints given herein, any typical values stated herein and/or any information regarding the application of the device, Infineon Technologies hereby disclaims any and all warranties and liabilities of any kind, including without limitation, warranties of non-infringement of intellectual property rights of any third party.

Information

For further information on technology, delivery terms and conditions and prices, please contact the nearest Infineon Technologies Office (<www.infineon.com>).

Warnings

Due to technical requirements, components may contain dangerous substances. For information on the types in question, please contact the nearest Infineon Technologies Office.
Infineon Technologies components may be used in life-support devices or systems only with the express written approval of Infineon Technologies, if a failure of such components can reasonably be expected to cause the failure of that life-support device or system or to affect the safety or effectiveness of that device or system. Life support devices or systems are intended to be implanted in the human body or to support and/or maintain and sustain and/or protect human life. If they fail, it is reasonable to assume that the health of the user or other persons may be endangered.

Looking for pricing, stock, or lifecycle information?

Click below to explore more details on WIN SOURCE:

- View MAX40007ANT+ on WIN SOURCE
- Analog Devices Inc. Information

Optimize Your Supply Chain with WIN SOURCE Solutions

- Global Sourcing Solution
- Obsolete Management
- Cost Control Management
- Shortage Management
- Alternative Solution
- Excess Inventory Management