THE DATASHEET OF

ZX5T951ZTA

ZXTP2013Z

100V PNP LOW SATURATION MEDIUM POWER TRANSISTOR IN SOT89

SUMMARY

BV_{CEO} = -100V : R_{SAT} = 57mΩ; I_C = -3.5A

DESCRIPTION

Packaged in the SOT89 outline this new low saturation 100V PNP transistor offers low on state losses making it ideal for use in DC-DC circuits, line switching and various driving and power management functions.



SOT89

FEATURES

- 3.5 amps continuous current
- Up to 10 amps peak current
- Very low saturation voltages

APPLICATIONS

- Motor driving
- Line switching
- High side switches
- Subscriber line interface cards (SLIC)



ORDERING INFORMATION

DEVICE	REEL SIZE	TAPE WIDTH	QUANTITY PER REEL
ZXTP2013ZTA	7"	12mm embossed	1,000 units

DEVICE MARKING

953

PINOUT



VIEW

ISSUE 1 - JUNE 2005

ABSOLUTE MAXIMUM RATINGS

PARAMETER	SYMBOL	LIMIT	UNIT
Collector-base voltage	BV_{CBO}	-140	V
Collector-emitter voltage	BV_{CEO}	-100	V
Emitter-base voltage	BV_{EBO}	-7	V
Continuous collector current[a]	I_C	-3.5	A
Peak pulse current	I_{CM}	-10	A
Power dissipation at T_A=25°C [a] Linear derating factor	P_D	1.5 12	W mW/°C
Power dissipation at T_A=25°C [b] Linear derating factor	P_D	2.1 16.8	W mW/°C
Operating and storage temperature range	T_j, T_{stg}	-55 to 150	°C

THERMAL RESISTANCE

PARAMETER	SYMBOL	LIMIT	UNIT
Junction to ambient[a]	$R_{\theta JA}$	83	°C/W
Junction to ambient[b]	$R_{\theta JA}$	60	°C/W

NOTES:
(a) For a device surface mounted on 25mm x 25mm x 1.6mm FR4 PCB with high coverage of single sided 1oz copper, in still air conditions.
(b) For a device surface mounted on 50mm x 50mm x 1.6mm FR4 PCB with high coverage of single sided 1oz copper, in still air conditions.

CHARACTERISTICS



ELECTRICAL CHARACTERISTICS (at T_{amb} = 25°C unless otherwise stated)

PARAMETER	SYMBOL	MIN.	TYP.	MAX.	UNIT	CONDITIONS
Collector-base breakdown voltage	BV_{CBO}	-140	-160		V	I_C = -100μA
Collector-emitter breakdown voltage	BV_{CER}	-140	-160		V	I_C = -1μA, RB ≤ 1kΩ
Collector-emitter breakdown voltage	BV_{CEO}	-100	-115		V	I_C = -10mA*
Emitter-base breakdown voltage	BV_{EBO}	-7	-8.1		V	I_E = -100μA
Collector cut-off current	I_{CBO}		<1	-20	nA	V_{CB} = -100V
				-0.5	μA	V_{CB} = -100V, T_{amb}=100°C
Collector cut-off current	I_{CER}		<1	-20	nA	V_{CB} = -100V
	R≤1kΩ			-0.5	μA	V_{CB} = -100V, T_{amb}=100°C
Emitter cut-off current	I_{EBO}		<1	-10	nA	V_{EB} = -6V
Collector-emitter saturation voltage	$V_{CE(SAT)}$		-20	-30	mV	I_C = -0.1A, I_B = -10mA*
			-65	-85	mV	I_C = -1A, I_B = -100mA*
			-110	-135	mV	I_C = -2A, I_B = -200mA*
			-230	-300	mV	I_C = -4A, I_B = -400mA*
Base-emitter saturation voltage	$V_{BE(SAT)}$		-970	-1060	mV	I_C = -4A, I_B = -400mA*
Base-emitter turn on voltage	$V_{BE(ON)}$		-910	-1030	mV	I_C = -4A, V_{CE} = -1V*
Static forward current transfer ratio	h_{FE}	100	250			I_C = -10mA, V_{CE} = -1V*
		100	200	300		I_C = -1A, V_{CE} = -1V*
		25	50			I_C = -3A, V_{CE} = -1V*
		15	30			I_C = -4A, V_{CE} = -1V*
			5			I_C = -10A, V_{CE} = -1V*
Transition frequency	f_T		125		MHz	I_C = 100mA, V_{CE} = 10V
						f=50MHz
Output capacitance	C_{OBO}		42		pF	V_{CB} = -10V, f= 1MHz*
Switching times	t_{ON}		42		ns	I_C = 1A, V_{CC} = 10V,
	t_{OFF}		540			I_{B1} = I_{B2} = 100mA

* Measured under pulsed conditions. Pulse width ≤ 300μs; duty cycle ≤ 2%.

TYPICAL CHARACTERISTICS



ZXTP2013Z

PACKAGE OUTLINE



PACKAGE DIMENSIONS

DIM	Millimeters		Inches		DIM	Millimeters		Inches	
	Min	Max	Min	Max		Min	Max	Min	Max
A	1.40	1.60	0.550	0.630	e	1.40	1.50	0.055	0.059
b	0.38	0.48	0.015	0.019	E	3.75	4.25	0.150	0.167
b1	-	0.53	-	0.021	E1	-	2.60	-	0.102
b2	1.50	1.80	0.060	0.071	G	2.90	3.00	0.114	0.118
c	0.28	0.44	0.011	0.017	H	2.60	2.85	0.102	0.112
D	4.40	4.60	0.173	0.181	-	-	-	-	-

© Zetex Semiconductors plc 2005

Europe

Zetex GmbH
Streitfeldstraße 19
D-81673 München
Germany

Telefon: (49) 89 45 49 49 0
Fax: (49) 89 45 49 49 49
europe.sales@zetex.com

Americas

Zetex Inc
700 Veterans Memorial Hwy
Hauppauge, NY 11788
USA

Telephone: (1) 631 360 2222
Fax: (1) 631 360 8222
usa.sales@zetex.com

Asia Pacific

Zetex (Asia) Ltd
3701-04 Metroplaza Tower 1
Hing Fong Road, Kwai Fong
Hong Kong

Telephone: (852) 26100 611
Fax: (852) 24250 494
asia.sales@zetex.com

Corporate Headquarters

Zetex Semiconductors plc
Zetex Technology Park
Chadderton, Oldham, OL9 9LL
United Kingdom

Telephone (44) 161 622 4444
Fax: (44) 161 622 4446
hq@zetex.com

These offices are supported by agents and distributors in major countries world-wide.

This publication is issued to provide outline information only which (unless agreed by the Company in writing) may not be used, applied or reproduced for any purpose or form part of any order or contract or be regarded as a representation relating to the products or services concerned. The Company reserves the right to alter without notice the specification, design, price or conditions of supply of any product or service.

For the latest product information, log on to www.zetex.com

ISSUE 1 - JUNE 2005

Looking for pricing, stock, or lifecycle information?

Click below to explore more details on WIN SOURCE:

- View ZX5T951ZTA on WIN SOURCE
- Diodes Incorporated Information

Optimize Your Supply Chain with WIN SOURCE Solutions

- Global Sourcing Solution
- Obsolete Management
- Cost Control Management
- Shortage Management
- Alternative Solution
- Excess Inventory Management