




# THE DATASHEET OF ZDT6757TA




# SM-8 COMPLEMENTARY MEDIUM POWER TRANSISTORS

ISSUE 1 - NOVEMBER 1995

## ZDT6757



PARTMARKING DETAIL - T6757



SM-8  
(8 LEAD SOT223)

### ABSOLUTE MAXIMUM RATINGS.

PARAMETER	SYMBOL	NPN	PNP	UNIT
Collector-Base Voltage	$V_{CB0}$	300	-300	V
Collector-Emitter Voltage	$V_{CE0}$	300	-300	V
Emitter-Base Voltage	$V_{EB0}$	5	-5	V
Peak Pulse Current	$I_{CM}$	1	-1	A
Continuous Collector Current	$I_C$	0.5	-0.5	A
Operating and Storage Temperature Range	$T_J; T_{stg}$	-55 to +150		$^{\circ}C$

### THERMAL CHARACTERISTICS

PARAMETER	SYMBOL	VALUE	UNIT
Total Power Dissipation at $T_{amb} = 25^{\circ}C$ * Any single die "on" Both die "on" equally	$P_{tot}$	2.25 2.75	W W
Derate above $25^{\circ}C$ * Any single die "on" Both die "on" equally		18 22	mW/ $^{\circ}C$ mW/ $^{\circ}C$
Thermal Resistance - Junction to Ambient* Any single die "on" Both die "on" equally		55.6 45.5	$^{\circ}C/W$ $^{\circ}C/W$

\* The power which can be dissipated assuming the device is mounted in a typical manner on a PCB with copper equal to 2 inches square.

### NPN TRANSISTOR ELECTRICAL CHARACTERISTICS


PARAMETER	SYMBOL	MIN	MAX
Collector-Base Breakdown Voltage	$V_{(BR)CB0}$	30	
Collector-Emitter Breakdown Voltage	$V_{(BR)CE0}$	30	
Emitter-Base Breakdown Voltage	$V_{(BR)EB0}$	5	
Collector Cutoff Current	$I_{CBO}$		
Emitter Cutoff Current	$I_{EBO}$		
Collector-Emitter Saturation Voltage	$V_{CE(sat)}$		
Base-Emitter Saturation Voltage	$V_{BE(sat)}$		
Base-Emitter Turn-On Voltage	$V_{BE(on)}$		
Static Forward Current Transfer Ratio	$h_{FE}$	50	40
Transition Frequency	$f_T$		30
Output Capacitance	$C_{obo}$		

\*Measured under pulsed conditions. Pulse For typical characteristics graphs see FZ16


# SM-8 COMPLEMENTARY MEDIUM POWER TRANSISTORS

ISSUE 1 - NOVEMBER 1995

## ZDT6757



PARTMARKING DETAIL - T6757



SM-8  
(8 LEAD SOT223)

### ABSOLUTE MAXIMUM RATINGS.

PARAMETER	SYMBOL	NPN	PNP	UNIT
Collector-Base Voltage	$V_{CB0}$	300	-300	V
Collector-Emitter Voltage	$V_{CE0}$	300	-300	V
Emitter-Base Voltage	$V_{EB0}$	5	-5	V
Peak Pulse Current	$I_{CM}$	1	-1	A
Continuous Collector Current	$I_C$	0.5	-0.5	A
Operating and Storage Temperature Range	$T_J; T_{stg}$	-55 to +150		$^{\circ}C$

### THERMAL CHARACTERISTICS

PARAMETER	SYMBOL	VALUE	UNIT
Total Power Dissipation at $T_{amb} = 25^{\circ}C$ * Any single die "on" Both die "on" equally	$P_{tot}$	2.25 2.75	W W
Derate above $25^{\circ}C$ * Any single die "on" Both die "on" equally		18 22	mW/ $^{\circ}C$ mW/ $^{\circ}C$
Thermal Resistance - Junction to Ambient* Any single die "on" Both die "on" equally		55.6 45.5	$^{\circ}C/W$ $^{\circ}C/W$

\* The power which can be dissipated assuming the device is mounted in a typical manner on a PCB with copper equal to 2 inches square.

### NPN TRANSISTOR ELECTRICAL CHARACTERISTICS

PARAMETER	SYMBOL	MIN	MAX
Collector-Base Breakdown Voltage	$V_{(BR)CB0}$	30	
Collector-Emitter Breakdown Voltage	$V_{(BR)CE0}$	30	
Emitter-Base Breakdown Voltage	$V_{(BR)EB0}$	5	
Collector Cutoff Current	$I_{CBO}$		
Emitter Cutoff Current	$I_{EBO}$		
Collector-Emitter Saturation Voltage	$V_{CE(sat)}$		
Base-Emitter Saturation Voltage	$V_{BE(sat)}$		
Base-Emitter Turn-On Voltage	$V_{BE(on)}$		
Static Forward Current Transfer Ratio	$h_{FE}$	50	40
Transition Frequency	$f_T$		30
Output Capacitance	$C_{obo}$		

\*Measured under pulsed conditions. Pulse  
For typical characteristics graphs see FZ16

# ZDT6757

## PNP TRANSISTOR ELECTRICAL CHARACTERISTICS (at $T_{amb} = 25^{\circ}\text{C}$ unless otherwise stated).

PARAMETER	SYMBOL	MIN.	TYP.	MAX.	UNIT	CONDITIONS.
Collector-Base Breakdown Voltage	$V_{(BR)CBO}$	-300			V	$I_C = -100\mu\text{A}, I_E = 0$
Collector-Emitter Breakdown Voltage	$V_{(BR)CEO}$	-300			V	$I_C = -10\text{mA}, I_B = 0^*$
Emitter-Base Breakdown Voltage	$V_{(BR)EBO}$	-5			V	$I_E = -100\mu\text{A}, I_C = 0$
Collector Cutoff Current	$I_{CBO}$			-100	nA nA	$V_{CE} = -160\text{V}, I_E = 0$ $V_{CE} = -200\text{V}, I_E = 0$
Emitter Cutoff Current	$I_{EBO}$			-100	nA	$V_{EB} = -3\text{V}, I_C = 0$
Collector-Emitter Saturation Voltage	$V_{CE(sat)}$			-0.5	V	$I_C = -100\text{mA}, I_B = -10\text{mA}^*$
Base-Emitter Saturation Voltage	$V_{BE(sat)}$			-1.0	V	$I_C = -100\text{mA}, I_B = -10\text{mA}^*$
Base-Emitter Turn-On Voltage	$V_{BE(on)}$			-1.0	V	$I_C = -100\text{mA}, V_{CE} = -5\text{V}^*$
Static Forward Current Transfer Ratio	$h_{FE}$	50 40				$I_C = -100\text{mA}, V_{CE} = -5\text{V}^*$ $I_C = -10\text{mA}, V_{CE} = -5\text{V}^*$
Transition Frequency	$f_T$	30			MHz	$I_C = -10\text{mA}, V_{CE} = -20\text{V}$ $f = 20\text{MHz}$
Output Capacitance	$C_{obo}$			20	pF	$V_{CB} = -20\text{V}, f = 1\text{MHz}$

\*Measured under pulsed conditions. Pulse width=300 $\mu$ s. Duty cycle  $\leq$  2%  
For typical characteristics graphs see FZT757 datasheet.

## Looking for pricing, stock, or lifecycle information?

Click below to explore more details on WIN SOURCE:

- ⊖ [View ZDT6757TA on WIN SOURCE](#)
- ⊖ [Diodes Incorporated Information](#)

## Optimize Your Supply Chain with WIN SOURCE Solutions

- ✓ Global Sourcing Solution
- ✓ Obsolete Management
- ✓ Cost Control Management
- ✓ Shortage Management
- ✓ Alternative Solution
- ✓ Excess Inventory Management