THE DATASHEET OF

MAX4550CAI+T

www.win-source.net 0086-755-83957316

19-1397; Rev 0; 10/98

EVALUATION KIT AVAILABLE

MAXIM

Serially Controlled, Dual 4x2, Clickless Audio/Video Analog Crosspoint Switches

General Description

The MAX4550/MAX4570 serial-interface, programmable, dual 4x2 audio/video crosspoint switches are ideal for multimedia applications. Each device contains two identical crosspoint switch arrays, each with four inputs and two outputs. To improve off-isolation, use the additional crosspoint inputs SA and SB as shunts. Each output is selectively programmable for clickless or regular mode operation. A set of internal resistive voltage-dividers supplies DC bias for each output when using AC-coupled inputs. Additionally, four auxiliary outputs control additional circuitry via the MAX4550/MAX4570's 2-wire or 3-wire interface.

The MAX4550/MAX4570 feature 80Ω on-resistance, 10Ω on-resistance matching between channels, 5Ω on-resistance flatness, and 0.014% total harmonic distortion. Additionally, they feature off-isolation of at least -110dB in the audio frequency range and -78dB at 4MHz, with -95dB crosstalk in the audio frequency range and -54dB at 4MHz. The MAX4550 uses a 2-wire I^2C-compatible serial interface, while the MAX4570 uses a 3-wire SPI™/QSPI™ or MICROWIRE™-compatible serial interface. These parts are available in 28-pin SSOP and wide SO packages and are tested over either the commercial (0°C to +70°C) or extended (-40°C to +85°C) operating temperature range.

Applications

Set-Top Boxes

PC Multimedia Boards

High-End Audio Systems

Video Conferencing Systems

Ordering Information

PART	TEMP. RANGE	PIN-PACKAGE
MAX4550CAI	0°C to +70°C	28 SSOP
MAX4550CWI	0°C to +70°C	28 Wide SO
MAX4550EAI	-40°C to +85°C	28 SSOP
MAX4550EWI	-40°C to +85°C	28 Wide SO
MAX4570CAI	0°C to +70°C	28 SSOP
MAX4570CWI	0°C to +70°C	28 Wide SO
MAX4570EAI	-40°C to +85°C	28 SSOP
MAX4570EWI	-40°C to +85°C	28 Wide SO

I^2C is a trademark of Philips Corp.
SPI/QSPI are trademarks of Motorola, Inc.
MICROWIRE is a trademark of National Semiconductor Corp.

Features

- ♦ **Selectable Soft Switching Mode for Clickless Audio Operation**
- ♦ **43Ω Typical On-Resistance (±5V Supplies)**
- ♦ **5Ω Typical On-Resistance Matching Between Channels**
- ♦ **4Ω Typical On-Resistance Flatness**
- ♦ **0.014% Total Harmonic Distortion with 1kΩ Load**
- ♦ **-110dB Off-Isolation at 20kHz**
  -78dB Off-Isolation at 4MHz
- ♦ **-95dB Crosstalk at 20kHz**
  -54dB Crosstalk at 4MHz
- ♦ **Serial Interface**
  2-Wire, Fast-Mode, I^2C-Compatible (MAX4550)
  3-Wire, SPI/QSPI/MICROWIRE-Compatible (MAX4570)
- ♦ **Four Auxiliary Outputs that Extend µP Ports**
- ♦ **Single-Supply Operation: +2.7V to +5.5V**
  Dual-Supply Operation: ±2.7V to ±5.5V

Pin Configuration



Functional Diagram appears at end of data sheet.

For free samples & the latest literature: http://www.maxim-ic.com, or phone 1-800-998-8800. For small orders, phone 1-800-835-8769.

Serially Controlled, Dual 4x2, Clickless Audio/Video Analog Crosspoint Switches

ABSOLUTE MAXIMUM RATINGS

V+ to GND ..... -0.3V to +6V
V+ to V- ..... -0.3V to +13.2V
V- to GND ..... +0.3V to -6V
NO_ _ , S_, BIAS_, COM_ _, Q_, A1, DOUT to GND (Note 1) ..... (V- - 0.3V) to (V+ + 0.3V)
$\overline{CS}$, SCLK, DIN, SCL, SDA, A0 to GND ..... -0.3V to +6V
Continuous Current into Any Terminal ..... ±10mA
Peak Current, NO_ _ , S_ , COM_ _ (pulsed at 1ms, 10% duty cycle max) ..... ±40mA

Continuous Power Dissipation (T_A = +70°C)
28-Pin SSOP (derate 9.52mW/°C above +70°C) 762mW
28-Pin Wide SO (derate 12.5mW/°C above +70°C) ... 1000mW
Operating Temperature Ranges
MAX4550C_I/MAX4570C_I ..... -0°C to +70°C
MAX4550E_I/MAX4570E_I ..... -40°C to +85°C
Storage Temperature Range ..... -65°C to +160°C
Lead Temperature (soldering, 10sec) ..... +300°C

Note 1: Signals on NO_ _, S_, or COM_ _ exceeding V+ or V- are clamped by internal diodes. Limit forward-diode current to maximum current rating.

Stresses beyond those listed under "Absolute Maximum Ratings" may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated in the operational sections of the specifications is not implied. Exposure to absolute maximum rating conditions for extended periods may affect device reliability.

ANALOG ELECTRICAL CHARACTERISTICS—Dual Supplies

(V+ = +5V ±5%, V- = -5V ±5%, T_A = T_{MIN} to T_{MAX}, unless otherwise noted. Typical values are at T_A = +25°C.) (Note 2)

PARAMETER	SYMBOL	CONDITIONS		MIN	TYP	MAX	UNITS
ANALOG SWITCHES							
Analog Signal Range (Note 3)	$V_{NO__}$, $V_{COM__}$, $V_{S_}$			V-		V+	V
On-Resistance	R_{ON}	$I_{COM__}$ = 4mA, $V_{NO__}$ or $V_{S_}$ = ±3.0V, V+ = 4.75V, V- = -4.75V	T_A = +25°C		43	80	Ω
			T_A = T_{MIN} to T_{MAX}			100	
COM_ _ to NO_ _ or S_ On-Resistance Match Between Channels (Note 4)	ΔR_{ON}	$I_{COM__}$ = 4mA, $V_{NO__}$ or $V_{S_}$ = ±3.0V, V+ = 4.75V, V- = -4.75V	T_A = +25°C		5	10	Ω
			T_A = T_{MIN} to T_{MAX}			10	
COM_ _ to NO_ _ or S_ On-Resistance Flatness (Note 5)	$\Delta R_{FLAT(ON)}$	$I_{COM__}$ = 4mA; $V_{NO__}$ or $V_{S_}$ = ±3.0V, 0; V+ = 4.75V; V- = -4.75V	T_A = +25°C		4	5	Ω
			T_A = T_{MIN} to T_{MAX}			8	
NO_ _ or S_ Off-Leakage Current (Note 6)	$NO_{_(OFF)}$	$V_{NO__}$ or $V_{S_}$ = ±4.5V, $V_{COM_}$ = ∓4.5V, V+ = 5.25V, V- = -5.25V	T_A = +25°C	-1	0.01	1	nA
			T_A = T_{MIN} to T_{MAX}	-10		10	
COM_ _ Off-Leakage Current (Note 6)	$I_{COM_(OFF)}$	$V_{NO__}$ or $V_{S_}$ = ±4.5V, $V_{COM_}$ = ∓4.5V, V+ = 5.25V, V- = -5.25V	T_A = +25°C	-5	0.01	5	nA
			T_A = T_{MIN} to T_{MAX}	-10		10	
COM_ _ On-Leakage Current (Note 6)	$I_{COM_(ON)}$	$V_{NO__}$ or $V_{S_}$ = floating, $V_{COM_}$ = ±4.5V, V+ = 5.25V, V- = -5.25V	T_A = +25°C	-5	0.01	5	nA
			T_A = T_{MIN} to T_{MAX}	-20		20	
AUDIO PERFORMANCE							
Total Harmonic Distortion plus Noise	THD+N	f_{IN} = 1kHz, R_L = 1kΩ, $V_{NO_}$ or $V_{S_}$ = $1V_{RMS}$, $V_{NO_}$ or $V_{S_}$ = 0			0.014		%
Off-Isolation (Note 7)	$V_{ISO(A)}$	V_{NO} = $1V_{RMS}$, f_{IN} = 20kHz, R_L = 10kΩ, S = GND	Shunt switch on		-110		dB
			Shunt switch off		-80		
Channel-to-Channel Crosstalk	$V_{CTA(A)}$	$V_{NO__}$ or $V_{S_}$ = $1V_{RMS}$, f_{IN} = 20kHz, R_L = 10kΩ, three channels driven at 20kHz			-95		dB

ANALOG ELECTRICAL CHARACTERISTICS—Dual Supplies (continued)

(V+ = +5V ±5%, V- = -5V ±5%, T_A = T_{MIN} to T_{MAX}, unless otherwise noted. Typical values are at T_A = +25°C.) (Note 2)

PARAMETER	SYMBOL	CONDITIONS		MIN	TYP	MAX	UNITS
VIDEO PERFORMANCE							
Off-Isolation	$V_{ISO(V)}$	$V_{NO__}$ or $V_{S_}$ = 1_{VRMS}, f_{IN} = 4MHz, R_L = 1kΩ, S_ = GND	Shunt switch on		-78		dB
			Shunt switch off		-63		
Channel-to-Channel Crosstalk	$V_{CT(V)}$	$V_{NO__}$ or $V_{S_}$ = 1_{VRMS}, f_{IN} = 4MHz, R_L = 10Ω, three channels driven at 4MHz			-54		dB
0.1dB Bandwidth	BW	R_S = 75Ω, R_L = 1kΩ			14		MHz
Off-Capacitance	$C_{OFF(NO)}$	f_{IN} = 1MHz,			11		pF
DYNAMIC TIMING WITH CLICKLESS MODE DISABLED (Note 8)							
Turn-On Time (Note 9)	t_{ONSD}	$V_{NO__}$ or $V_{S_}$ = 1.5V, R_L = 5kΩ			400	900	ns
Turn-Off Time (Note 9)	t_{OFFSD}	$V_{NO__}$ or $V_{S_}$ = 1.5V, R_L = 300Ω			200	500	ns
Break-Before-Make Time	t_{BBM}	$V_{NO__}$ or $V_{S_}$ = 1.5V		10	100		ns
DYNAMIC TIMING WITH CLICKLESS MODE ENABLED (Note 8, Figure 5)							
Turn-On Time	t_{ONSE}	$V_{NO__}$ or $V_{S_}$ = 1.5V, R_L = 5kΩ			36		ms
Turn-Off Time	t_{OFFSE}	$V_{NO__}$ or $V_{S_}$ = 1.5V, R_L = 300Ω			11		ms
BIAS NETWORKS							
Bias Network Resistance	R_{BIAS}	BIASH to BIASL		13	20	27	kΩ
POWER SUPPLIES							
Supply Voltage Range	V+			2.7		5.25	V
	V-			-5.25		0	
V+ Supply Current (Note 10)	I+	Reset condition, V+ = 2.7V to 5.25V			7	20	µA
V- Supply Current	I-	Reset condition, V- = -5.25V to 0				-20	µA

ANALOG ELECTRICAL CHARACTERISTICS—Single +5V Supply

(V+ = +5V ±5%, V- = 0, T_A = T_{MIN} to T_{MAX}, unless otherwise noted. Typical values are at T_A = +25°C.) (Note 2)

PARAMETER	SYMBOL	CONDITIONS		MIN	TYP	MAX	UNITS
ANALOG SWITCHES							
Analog Signal Range (Note 3)	$V_{NO__}$, $V_{COM__}$, $V_{S_}$			0		V+	V
On-Resistance	R_{ON}	$I_{COM__}$ = 4mA, $V_{NO__}$ or $V_{S_}$ = 3.0V, V+ = 4.75V	T_A = +25°C		60	100	Ω
			T_A = T_{MIN} to T_{MAX}			130	
On-Resistance Match Between Channels (Note 4)	ΔR_{ON}	$I_{COM__}$ = 4mA, $V_{NO__}$ or $V_{S_}$ = 3.0V, V+ = 4.75V	T_A = +25°C		5	10	Ω
			T_A = T_{MIN} to T_{MAX}			10	
On-Resistance Flatness (Note 5)	R_{FLAT}	$I_{COM__}$ = 4mA; $V_{NO__}$ or $V_{S_}$ = 1V, 2V, 3V; V+ = 4.75V	T_A = +25°C		4	10	Ω
			T_A = T_{MIN} to T_{MAX}			15	
NO_ _ or S_ Off-Leakage Current (Notes 6, 11)	$I_{NO__(OFF)}$	V_{NO} or $V_{S_}$ = 4.5V, 1V; $V_{COM__}$ = 1V, 4.5V; V+ = 5.25V	T_A = +25°C	-1	0.01	1	nA
			T_A = T_{MIN} to T_{MAX}	-10		10	

Serially Controlled, Dual 4x2, Clickless Audio/Video Analog Crosspoint Switches

ANALOG ELECTRICAL CHARACTERISTICS—Single +5V Supply (continued)

(V+ = +5V ±5%, V- = 0, T_A = T_{MIN} to T_{MAX}, unless otherwise noted. Typical values are at T_A = +25°C.) (Note 2)

PARAMETER	SYMBOL	CONDITIONS		MIN	TYP	MAX	UNITS
COM_ _ Off-Leakage Current (Notes 6, 11)	$I_{COM__(OFF)}$	$V_{NO__}$ or $V_{S_}$ = 4.5V, 1V; $V_{COM__}$ = 1V, 4.5V; V+ = 5.25V	T_A = +25°C	-5	0.01	5	nA
			T_A = T_{MIN} to T_{MAX}	-10		10	
COM_ _ On-Leakage Current (Notes 6, 11)	$I_{COM__(ON)}$	$V_{NO__}$ or $V_{S_}$ = floating; $V_{COM__}$ = 1V, 4.5V; V+ = 5.25V	T_A = +25°C	-5	0.01	5	nA
			T_A = T_{MIN} to T_{MAX}	-20		20	
AUDIO PERFORMANCE							
Total Harmonic Distortion plus Noise	THD+N	f_{IN} = 1kHz, R_L = 10kΩ, $V_{NO__}$ or $V_{S_}$ = $1V_{RMS}$, $V_{NO__}$ or $V_{S_}$ = 2.5V			0.014		%
Off-Isolation (Note 7)	$V_{ISO(A)}$	$V_{NO__}$ or $V_{S_}$ = $1V_{RMS}$, f_{IN} = 20kHz, R_L = 10kΩ, S = GND	Shunt switch on		-105		dB
			Shunt switch off		-80		
Channel-to-Channel Crosstalk	$V_{TC(A)}$	$V_{NO__}$ or $V_{S_}$ = $1V_{RMS}$, f_{IN} = 20kHz, R_L = 10kΩ, three channels driven at 20kHz			-97		dB
VIDEO PERFORMANCE							
Off-Isolation (Note 7)	$V_{ISO(V)}$	$V_{NO__}$ or $V_{S_}$ = $1V_{RMS}$, f_{IN} = 4MHz, R_L = 1kΩ, S = GND	Shunt switch on		-74		dB
			Shunt switch off		-61		
Channel-to-Channel Crosstalk	$V_{TC(V)}$	$V_{NO__}$ or $V_{S_}$ = $1V_{RMS}$, f_{IN} = 4MHz, R_L = 10kΩ, three channels driven at 4MHz			-52		dB
0.1dB Bandwidth	BW	R_{SOURCE} = 75Ω, R_L = 1kΩ			13		MHz
Off-Capacitance	$C_{OFF(NO)}$	f_{IN} = 1MHz			11		pF
DYNAMIC TIMING WITH CLICKLESS MODE DISABLED (Note 8)							
Turn-On Time (Note 9)	t_{ONSD}	$V_{NO__}$ or $V_{S_}$ = 1.5V, R_L = 5kΩ			400	900	ns
Turn-Off Time (Note 9)	t_{OFFSD}	$V_{NO__}$ or $V_{S_}$ = 1.5V, R_L = 300Ω			160	500	ns
Break-Before-Make Time	t_{BBM}	$V_{NO__}$ or $V_{S_}$ = 1.5V		10	100		ns
DYNAMIC TIMING WITH CLICKLESS MODE ENABLED (Note 8, Figure 5)							
Turn-On Time	t_{ONSE}	$V_{NO__}$ or $V_{S_}$ = 1.5V, R_L = 5kΩ			43		ms
Turn-Off Time	t_{OFFSE}	$V_{NO__}$ or $V_{S_}$ = 1.5V, R_L = 300Ω			14		ms
BIAS NETWORKS							
Bias Network Resistance	R_{BIAS}	BIASH to BIASL		13	20	27	kΩ

ANALOG ELECTRICAL CHARACTERISTICS—Single +3V Supply

(V+ = +3V ±10%, V- = 0, T_A = T_{MIN} to T_{MAX}, unless otherwise noted. Typical values are at T_A = +25°C.) (Note 2)

PARAMETER	SYMBOL	CONDITIONS		MIN	TYP	MAX	UNITS
ANALOG SWITCHES							
Analog Signal Range (Note 3)	$V_{NO__}$, $V_{COM__}$, $V_{S_}$			0		V+	V
On-Resistance	R_{ON}	$I_{COM__}$ = 4mA, $V_{NO__}$ or $V_{S_}$ = 1V, V+ = 2.7V	T_A = +25°C		106	180	Ω
			T_A = T_{MIN} to T_{MAX}			220	

INTERFACE I/O CHARACTERISTICS

(V+ = +2.7V to +5.5V, V- = 0 to -5.5V, T_A = T_{MIN} to T_{MAX}, unless otherwise noted. Typical values are at T_A = +25°C.) (Note 2)

PARAMETER	SYMBOL	CONDITIONS		MIN	TYP	MAX	UNITS
AUXILIARY OUTPUTS							
Output High Voltage	V_{OH}	I_{SOURCE} = 1mA to GND, V+ = 4.75V		4.45	4.65		V
		I_{SOURCE} = 0.5mA to GND, V+ = 2.7V		2.3	2.5		
Output Low Voltage	V_{OL}	I_{SINK} = 6mA, V+ = 2.7V			0.5	1.0	V
		I_{SINK} = 12mA, V+ = 4.75V			0.5	1.0	
DIGITAL INPUTS (SCK, DIN, $\overline{CS}$, SCL, SDA)							
Input High Voltage	V_{IH}	V+ > 3.6V		3.0			V
		V+ < 3.6V		2.0			
Input Low Voltage	V_{IL}	V+ > 3.6V				0.8	V
		V+ < 3.6V				0.6	
Input Hysteresis	V_{HYST}				0.2		V
Input Leakage Current (Note 7)	I_{LEAK}	$V_{NO__}$ = 0 or 5V		-1	0.01	1	µA
Input Capacitance	C_{NO}				5		pF
DIGITAL OUTPUTS (DOUT, SDA)							
Output Low Voltage	V_{OL}	I_{SINK} = 6mA	V+ = 4.75V			0.4	V
			V+ = 2.7V			0.8	
DOUT Output High Voltage	V_{OH}	I_{SOURCE} = 0.5mA		V+ - 0.5	V+ - 0.1		V
I^2C TIMING (V+ = +4.75V to +5.25V, Figures 1, 2)							
SCL Clock Frequency	f_{SCL}			DC		400	kHz
Bus Free Time between Stop and Start Condition	t_{BUF}			1.3			µs
STOP Condition Setup Time	$t_{SU:STO}$			0.6			µs
Data Hold Time	$t_{HD:DAT}$			0		0.9	µs
Data Setup Time	$t_{SU:DAT}$			100			ns
Clock Low Period	t_{LOW}			1.3			µs
Clock High Period	t_{HIGH}			0.6			µs
SCL/SDA Rise Time (Note 12)	t_R			20 + 0.1Cb		300	ns
SCL/SDA Fall Time (Note 12)	t_F			20 + 0.1Cb		300	ns
SPI TIMING (V+ = +4.75V to +5.25V, Figures 3, 4)							
Operating Frequency	f_{OP}			DC		2.1	MHz
DIN to SCLK Setup	f_{DS}			100			ns
DIN to SCLK Hold	f_{DH}					0	ns
SCLK Fall to Output Data Valid	f_{DO}	C_{LOAD} = 50pF		20		200	ns
$\overline{CS}$ to SCLK Rise Setup	f_{CSS}			100			ns
$\overline{CS}$ to SCLK Rise Hold	f_{CSH}			0			ns

Serially Controlled, Dual 4x2, Clickless Audio/Video Analog Crosspoint Switches

INTERFACE I/O CHARACTERISTICS (continued)

(V+ = +2.7V to +5.5V, V- = 0 to -5.5V, T_A = T_{MIN} to T_{MAX}, unless otherwise noted. Typical values are at T_A = +25°C.) (Note 2)

PARAMETER	SYMBOL	CONDITIONS	MIN	TYP	MAX	UNITS
SCLK Pulse Width Low	t_{CH}		200			ns
SCLK Pulse Width High	t_{CL}		200			ns
Rise Time (SCLK, DIN, $\overline{CS}$)	t_R				2.0	µs
Fall Time (SCLK, DIN, $\overline{CS}$)	t_F				2.0	µs

Note 2: The algebraic convention is used in this data sheet; the most negative value is shown in the minimum column.
Note 3: Guaranteed by design. Not subject to production testing.
Note 4: $\Delta R_{ON} = R_{ON(MAX)} - R_{ON(MIN)}$.
Note 5: On-resistance flatness is defined as the difference between the maximum and minimum on-resistance values, as measured over the specified analog signal range.
Note 6: Leakage parameters are 100% tested at maximum rated temperature, and guaranteed by correlation at T_A = +25°C.
Note 7: Off-isolation = 20 · log ($V_{COM__}$ / $V_{NO__}$), $V_{COM__}$ = output, $V_{NO__}$ = input to off switch.
Note 8: All timing is measured from the clock's falling edge preceding the ACK signal for 2-wire, and from $\overline{CS}$'s rising edge for 3-wire. Turn-Off Time is defined as the output of the switch for 0.5V change, tested with a 300Ω load to ground. Turn-On Time is measured with a 5kΩ load resistor to GND. All timing is shown with respect to 20% of V+ and 70% of V+, unless otherwise noted.
Note 9: Typical values are for MAX4570 only.
Note 10: Supply current can be as high as 2mA per switch during switch transitions in the clickless mode, corresponding to 40mA total supply transient current requirement.
Note 11: Leakage testing for single-supply operation is guaranteed by testing with dual supplies.
Note 12: Cb = capacitance of one bus line in pF. Tested with Cb = 400pF.

Typical Operating Characteristics

(T_A = +25°C, unless otherwise noted.)

ON-RESISTANCE vs. V_{COM} (DUAL SUPPLIES)



ON-RESISTANCE vs. V_{COM} AND TEMPERATURE (DUAL SUPPLIES)



ON-RESISTANCE vs. V_{COM} (SINGLE SUPPLY)



Typical Operating Characteristics (continued)

(T_A = +25°C, unless otherwise noted.)

ON-RESISTANCE vs. V_{COM} AND TEMPERATURE (SINGLE SUPPLY)



ON-RESISTANCE vs. TEMPERATURE



LEAKAGE CURRENT vs. TEMPERATURE



SUPPLY CURRENT vs. TEMPERATURE (DUAL SUPPLIES)



SUPPLY CURRENT vs. TEMPERATURE (SINGLE SUPPLY)



CHARGE INJECTION vs. V_{COM}



TURN-ON/TURN-OFF TIMES vs. SUPPLY VOLTAGE (DUAL SUPPLIES)



TURN-ON/TURN-OFF TIMES vs. SUPPLY VOLTAGE (SINGLE SUPPLY)



OFF-ISOLATION AND CROSSTALK vs. FREQUENCY



Serially Controlled, Dual 4x2, Clickless Audio/Video Analog Crosspoint Switches

Typical Operating Characteristics (continued)

(T_A = +25°C, unless otherwise noted.)

FREQUENCY RESPONSE



FREQUENCY RESPONSE



TOTAL HARMONIC DISTORTION PLUS NOISE vs. FREQUENCY



COM RISE TIME (SOFT MODE)



COM FALL TIME (SOFT MODE)



COM TURN-ON TIME (HARD MODE)



COM TURN-OFF TIME (HARD MODE)



COM TURN-ON TIME (SOFT MODE)



COM TURN-OFF TIME (SOFT MODE)



Pin Description

PIN		NAME	FUNCTION
MAX4550	MAX4570		
1	1	SB	Shunt Input to Crosspoint B. Use for shunt capacitor or AC ground connection to improve off-isolation, or as an additional input to switch matrix B.
2	2	NO3A	Input 3 to Crosspoint A
3	3	NO3B	Input 3 to Crosspoint B
4	4	BIASH	High Side of Bias Network. Use to give the outputs a DC bias when inputs are AC-coupled (refer to the *Using the Internal Bias Resistors* section).
5	5	BIASL	Low Side of Bias Network. Use to give the outputs a DC bias when inputs are AC-coupled (refer to the *Using the Internal Bias Resistors* section).
6	6	NO4A	Input 4 to Crosspoint A
7	7	NO4B	Input 4 to Crosspoint B
8, 24	8, 24	V+	Positive Supply Voltage. Supply range is +2.7V to +5.25V. Connect pin 8 to pin 24 externally.
9	9	COM2A	Output 2 of Crosspoint A
10	10	Q0	Auxiliary Output 0
11	11	COM2B	Output 2 of Crosspoint B
12	12	Q1	Auxiliary Output 1
13	—	A0	LSB+1 of 2-Wire Serial-Interface Address Field
—	13	$\overline{CS}$	Chip Select of 3-Wire Interface. Logic low on $\overline{CS}$ enables serial data to be clocked in to device. Programming commands are executed on $\overline{CS}$'s rising edge.
14	—	SCL	2-Wire Serial-Interface Clock Input
—	14	SCLK	3-Wire Serial-Interface Clock Input
15	—	SDA	2-Wire Serial-Interface Data Input. Data is clocked in on SCL's rising edge.
—	15	DIN	3-Wire Serial-Interface Data Input. Data is clocked in on SCLK's rising edge.
16	—	A1	LSB+2 of 2-Wire Serial-Interface Address Field
—	16	DOUT	Data Output of 3-Wire Interface. Input data is clocked out and SCLK's falling edge delayed by 16 clock cycles. DOUT remains active when $\overline{CS}$ is high.
17	17	Q2	Auxiliary Output 2
18	18	COM1B	Output 1 of Crosspoint A
19	19	Q3	Auxiliary Output 3
20	20	COM1A	Output 1 of Crosspoint A
21	21	GND	Ground
22	22	NO1A	Input 1 to Crosspoint A
23	23	NO1B	Input 1 to Crosspoint B
25	25	V-	Negative Supply Voltage. Supply range is from -5.25V to 0.
26	26	NO2A	Input 2 to Crosspoint A
27	27	NO2B	Input 2 to Crosspoint B
28	28	SA	Shunt Input to Crosspoint A. Use for shunt capacitor or AC ground connection to improve off-isolation, or as an additional input to switch matrix A.

Serially Controlled, Dual 4x2, Clickless Audio/Video Analog Crosspoint Switches

Detailed Description

The MAX4550/MAX4570 are serial-interface, programmable, dual 4x2 audio/video crosspoint switches. Each device contains two independent 4x2 crosspoint switches, controlled through the on-chip serial interface. The MAX4550 uses a 2-wire I^2C-compatible serial communications protocol, while the MAX4570 uses a 3-wire SPI/QSPI/MICROWIRE-compatible serial communications protocol.

These ICs include four controllable auxiliary outputs, each capable of sourcing 1mA or sinking 12mA. Also included are four selectable bias-resistor networks (one for each output) for use with AC-coupled input signals. Both devices operate with either ±5V dual supplies or a single +5V supply, and are optimized for use in the audio frequency range to 20kHz and at video frequencies up to 4MHz. They feature 80Ω on-resistance, 10Ω on-resistance matching between channels, 5Ω on-resistance flatness, and as low as 0.004% total harmonic distortion.

The MAX4550/MAX4570 offer better than -110dB of audio off-isolation, -95dB of audio crosstalk, -78dB of video off-isolation, and -54dB of video crosstalk (4MHz). The SA and SB (shunt) inputs further improve off-isolation, allowing for the addition of external shunt capacitors or the connection of outputs to AC grounds. These devices feature a clickless operation mode for noiseless audio switching. Clickless or standard switching mode is selectable for each individual output using the serial interface.

Applications Information

The MAX4550/MAX4570 are divided into five functional blocks: the control-logic block, two switch-matrix blocks, the bias-resistor block, and the auxiliary-output block (see *Functional Diagram*). The control-logic block accepts commands via the serial interface and uses those commands to control the four remaining blocks.

Command-Byte and Data-Byte Programming

The devices are programmed through their serial interface with a command byte followed by a data byte. Each bit of the command byte selects one of the functional blocks to be controlled by the subsequent data byte. The data byte sets the state of the selected block(s). For the two switch-matrix blocks, the data byte sets the switch state. For the bias-resistor block, the data byte controls which bias network is active. For the auxiliary-output block, the data byte programs the state of the four auxiliary outputs (see *Functional Diagram*).

A logic “1” in any bit position of the data byte makes that function active, while a logic “0” makes it inactive. Tables 1–4 describe the command byte and the corresponding data byte. For example, if bit C4 of the command byte is set, the subsequent data byte programs the state of the auxiliary outputs. If bits D0 and D2 of the subsequent data byte are set, Q0 and Q2 outputs are set high. If more than one bit of the command byte is set, the data byte programs **all** of the corresponding blocks. This operation is useful, for instance, to simultaneously set both switch matrices to the same configuration. Any block that is not selected in the command byte remains unchanged.

Table 1. Command-Byte Format

BIT	REGISTER
C7	Don’t care
C6	Don’t care
C5	BIAS/MODE
C4	AUX
C3	COM2B
C2	COM1B
C1	COM2A
C0	COM1A

Table 2. COM Data-Byte Format (C0, C1, C2, C3 = “1”)

BIT	DESCRIPTION
D7	Don’t care
D6	Don’t care
D5	Don’t care
D4	Controls the switch connected to S_ ; 1 = close switch, 0 = open switch.
D3	Controls the switch connected to NO4_ ; 1 = close switch, 0 = open switch.
D2	Controls the switch connected to NO3_ ; 1 = close switch, 0 = open switch.
D1	Controls the switch connected to NO2_ ; 1 = close switch, 0 = open switch.
D0	Controls the switch connected to NO1_ ; 1 = close switch, 0 = open switch.

Table 3. AUX_ Data-Byte Format (C4 = "1")

BIT	DESCRIPTION
D7	Don't care
D6	Don't care
D5	Don't care
D4	Don't care
D3	Controls output Q3; 1 = set output high, 0 = set output low.
D2	Controls output Q2; 1 = set output high, 0 = set output low.
D1	Controls output Q1; 1 = set output high, 0 = set output low.
D0	Controls output Q0; 1 = set output high, 0 = set output low.

Table 4. Clickless Mode/BIAS_ Data-Byte Format (C5 = "1")

BIT	DESCRIPTION
D7	Controls COM2B clickless mode; 1 = enables clickless mode, 0 = disables clickless mode.
D6	Controls COM1B clickless mode; 1 = enables clickless mode, 0 = disables clickless mode.
D5	Controls COM2A clickless mode; 1 = enables clickless mode, 0 = disables clickless mode.
D4	Controls COM1A clickless mode; 1 = enables clickless mode, 0 = disables clickless mode.
D3	Controls COM2B bias resistors; 1 = connect bias resistors, 0 = disconnect bias resistors.
D2	Controls COM1B bias resistors; 1 = connect bias resistors, 0 = disconnect bias resistors.
D1	Controls COM2A bias resistors; 1 = connect bias resistors, 0 = disconnect bias resistors.
D0	Controls COM1A bias resistors; 1 = connect bias resistors, 0 = disconnect bias resistors.

2-Wire Serial Interface

The MAX4550 uses a 2-wire, fast-mode, I^2C-compatible serial interface. This protocol consists of an address byte followed by the command and data bytes. To address a given chip, the A0 and A1 bits in the address byte must duplicate the values present at the A0 and A1 pins of that chip. The rest of the address bits control MAX4550 operation. The command and data-byte details are described in the *Command-Byte and Data-Byte Programming* section.

The 2-wire serial interface requires only two I/O lines of a standard microprocessor port. Figures 1 and 2 detail the timing diagram for signals on the 2-wire bus, and Table 5 details the format of the signals. The MAX4550 is a receive-only device and must be controlled by a bus master device. A bus master device communicates by transmitting the address byte of the slave device over the bus and then transmitting the desired information. Each transmission consists of a start condition, the MAX4550's programmable slave-address byte, a command-byte, a data-byte, and finally a stop condition. The slave device acknowledges the recognition of its address by pulling the SDA line low for one clock period after the address byte is transmitted. The slave device also issues a similar acknowledgment after the command byte and again after the data byte.

Start and Stop Conditions

The bus-master signals the beginning of a transmission with a start condition by transitioning SDA from high to low while SCL is high. When the master has finished communicating with the slave, it issues a stop condition by transitioning SDA from low to high while SCL is high. The bus is then free for another transmission.

Slave Address (Address Byte)

The MAX4550 uses an 8-bit-long slave address. To select a slave address, connect A0 and A1 to V+ or GND. The MAX4550 has four possible slave addresses, thus a maximum of four of these devices may share the same 2-bit address bus. The slave device (MAX4550) monitors the serial bus continuously, waiting for a start condition followed by an address byte. When a slave device recognizes its address ($10011A_1A_00$), it acknowledges that it is ready for further communication by pulling the SDA line low while SCL is high.

3-Wire Serial Interface

The MAX4570 3-wire serial interface is SPI/QSPI/MICROWIRE-compatible. An active-low chip-select ($\overline{CS}$) input enables the device to receive data from the serial input (DIN). Data is clocked in on the rising edge of the serial-clock (SCLK) signal. A total of 16 bits are needed in each write cycle. Segmented write cycles are allowed (two 8-bit-wide transfers) if $\overline{CS}$ remains low. The first bit clocked into the MAX4550 is the command byte's MSB, and the last bit clocked in is the data byte's LSB. While shifting data, the device remains in its original configuration. After all 16 bits are clocked into the input shift register, a rising edge on $\overline{CS}$ latches the data into the MAX4570 internal registers, initiating the device's change of state.

Serially Controlled, Dual 4x2, Clickless Audio/Video Analog Crosspoint Switches

Table 5. 2-Wire Serial-Interface Data Format

	ADDRESS BYTE									COMMAND BYTE									DATA BYTE									
	A7	A6	A5	A4	A3	A2	A1	A0		C7	C6	C5	C4	C3	C2	C1	C0		D7	D6	D5	D4	D3	D2	D1	D0		
SRT	1	0	0	1	1	A1	A0	0	ACK	X	X	BIAS	AUX	COM2B	COM1B	COM2A	COM1A	ACK	D7	D6	D5	D4	D3	D2	D1	D0	ACK	STOP

X = Don't care
SRT = Start condition
ACK = Acknowledge condition
STOP = Stop condition



Figure 1. 2-Wire Serial-Interface Timing Diagram



Figure 2. 2-Wire Serial-Interface Timing Details

Figures 3, 4, and Table 6 show the details of the 3-wire protocol, as it applies to the MAX4570. DOUT is the shift register's output. Data at DOUT is simply the input data delayed by 16 clock cycles, with data appearing synchronous with SCLK's falling edge. Transitions at DIN and SCLK have no effect when $\overline{CS}$ is high, and DOUT holds the last bit in the shift register.

Daisy Chaining

To program several MAX4570s, "daisy chain" the devices by connecting DOUT of the first device to DIN of the second, and so on. The $\overline{CS}$ pins of all devices are connected together, and data is shifted through the MAX4570s in series. 16 bits of data per device are required for proper programming of all devices. When $\overline{CS}$ is brought high, all devices are updated simultaneously.



Figure 3. 3-Wire Serial-Interface Communication



Figure 4. 3-Wire Serial-Interface Timing Details

Table 6. 3-Wire Serial-Interface Data Format

COMMAND BYTE								DATA BYTE							
MSB															LSB
C7	C6	C5	C4	C3	C2	C1	C0	D7	D6	D5	D4	D3	D2	D1	D0
X	X	BIAS	AUX	COM2B	COM1B	COM2A	COM1A	D7	D6	D5	D4	D3	D2	D1	D0

X = Don't care

Addressable Serial Interface

To program several MAX4570s individually using a single processor, connect DIN of each MAX4570 together and control $\overline{CS}$ on each MAX4570 separately. To select a particular device, drive the corresponding $\overline{CS}$ low, clock in the 16-bit command, then drive $\overline{CS}$ high and execute the command. Typically, only one MAX4570 is addressed at a time.

Improving Off-Isolation

To improve off-isolation, connect the SA or SB input to ground either directly (DC ground) or through capacitors (AC ground). Closing SA or SB effectively grounds the unused outputs.

Using the Internal Bias Resistors

Use the internal bias-resistor networks to give the switch outputs a DC bias when the switch terminals are AC coupled. Programming of the switches that connect the bias resistors to the outputs is accomplished via bit C5 of the command byte. Connect the BIASH and BIASL inputs to DC levels (for example, V+ and GND), and activate the switch connecting the appropriate output. This applies a voltage midway between V_{BIASH} and V_{BIASL} to the output (refer to Tables 1, 4, and the *Functional Diagram*).

Using the Auxiliary Outputs

The four auxiliary outputs provide a way to control external circuitry, such as LEDs or other DC loads, through the serial interface. Program these outputs via bit C4 of the command byte. Each output is capable of sourcing 1mA or sinking 12mA. They are programmed through the command byte and data byte (refer to Tables 1, 3, and the *Functional Diagram*).

Clickless Switching

Audible switching transients ("clicks") are eliminated in this mode of operation. When an output is configured as "clickless," the gate signal of the switches connected to that output are controlled with slow-moving voltages. As a result, the output slew rates are significantly reduced. Program clickless operation via bit C5 of the command byte (refer to Tables 1, 4, and the *Functional Diagram*). Each operating switch may draw as much as 2mA during transition.

Power-Up State

The MAX4550/MAX4570 feature a preset power-up state. Upon power-up, COM1A and COM2A are connected to SA, COM1B and COM2B are connected to SB, all outputs are set to clickless mode, all bias-resistor networks are disconnected from the outputs, and all auxiliary outputs are low. All other switches are open.

Functional Diagram



( ) ARE FOR MAX4570

Serially Controlled, Dual 4x2, Clickless Audio/Video Analog Crosspoint Switches

Package Information

SSOP.EPS



DIM	INCHES MIN	INCHES MAX	MILLIMETERS MIN	MILLIMETERS MAX
A	0.068	0.078	1.73	1.99
A1	0.002	0.008	0.05	0.21
B	0.010	0.015	0.25	0.38
C	0.004	0.008	0.09	0.20
D	SEE VARIATIONS			
E	0.205	0.209	5.20	5.38
e	0.0256 BSC		0.65 BSC	
H	0.301	0.311	7.65	7.90
L	0.025	0.037	0.63	0.95
α	0°	8°	0°	8°

	INCHES MIN	INCHES MAX	MILLIMETERS MIN	MILLIMETERS MAX	
D	0.239	0.249	6.07	6.33	14L
D	0.239	0.249	6.07	6.33	16L
D	0.278	0.289	7.07	7.33	20L
D	0.317	0.328	8.07	8.33	24L
D	0.397	0.407	10.07	10.33	28L





NOTES:
1. D&E DO NOT INCLUDE MOLD FLASH.
2. MOLD FLASH OR PROTRUSIONS NOT TO EXCEED .15mm (.006")
3. CONTROLLING DIMENSION: MILLIMETER

MAXIM
PROPRIETARY INFORMATION

TITLE:
PACKAGE OUTLINE, SSOP, 5.3X.65mm

APPROVAL	DOCUMENT CONTROL NO.	REV	
	21-0056	A	1/1

Maxim cannot assume responsibility for use of any circuitry other than circuitry entirely embodied in a Maxim product. No circuit patent licenses are implied. Maxim reserves the right to change the circuitry and specifications without notice at any time.

© 1998 Maxim Integrated Products Printed USA MAXIM is a registered trademark of Maxim Integrated Products.

Looking for pricing, stock, or lifecycle information?

Click below to explore more details on WIN SOURCE:

- View MAX4550CAI+T on WIN SOURCE
- Maxim Integrated Information

Optimize Your Supply Chain with WIN SOURCE Solutions

- Global Sourcing Solution
- Obsolete Management
- Cost Control Management
- Shortage Management
- Alternative Solution
- Excess Inventory Management