



**THE DATASHEET OF
LB11867RV-TLM-H**



Product Overview

LB11867RV: Variable Speed Single-Phase Fan Motor

For complete documentation, see the data sheet.

LB11867RV is a single-phase bipolar driving motor pre-driver with the variable speed function compatible with external PWM signal. With a few external parts, a highly-efficient and highly-silent variable drive fan motor with low power consumption can be achieved. This product is best suited for driving of the server requiring large air flow and large current and the fan motor of consumer appliances.

Features

- Single-phase full-wave driving pre-driver
- Variable speed control possible with external PWM input
- Current limiting circuit incorporated
- Reactive current cut circuit incorporated
- Minimum speed setting pin
- Soft start setting pin
- Lock protection and automatic reset circuits incorporated
- RD (lock detection) output
- Thermal shutdown circuit incorporated

Benefits



- High-efficiency low power-consumption drive

End Products

Part Electrical Specifications											
Product	Compliance	Status	Phase	V _M Min (V)	V _M Max (V)	V _{CC} Min (V)	V _{CC} Max (V)	I _O Max (A)	I _O Peak Max (A)	Control Type	Package Type
LB11867RV-TLM-E	Pb-free	Active	1			5.5	16	0.02		PWM	SSOP-16
LB11867RV-TLM-H	Pb-free Halide free	Active	1			5.5	16	0.02		PWM	SSOP-16
LB11867RV-W-AH	Pb-free Halide free	Active	1			5.5	16	0.02		PWM	SSOP-16

Looking for pricing, stock, or lifecycle information?

Click below to explore more details on WIN SOURCE:

-  [View LB11867RV-TLM-H on WIN SOURCE](#)
-  [ON Semiconductor](#) Information

Optimize Your Supply Chain with WIN SOURCE Solutions

-  Global Sourcing Solution
-  Obsolete Management
-  Cost Control Management
-  Shortage Management
-  Alternative Solution
-  Excess Inventory Management